



DESCRIPTION	COLOR	WIRE GAUGE	PIN
EMPTY	---	---	A1
FUEL PUMP RELAY OUT (10A MAX)	RED	20 ga IF RELAY TRIGGER	A2
INPUT #2 (FS2THG)	WHITE/RED	20 ga	A3
INPUT #4 (F,G,5)	WHITE/ GREEN	20 ga	A4
TPS SIGNAL	GREEN	20 ga	A5
POINTS OUTPUT	WHITE	18 ga	A6
WBI_COMPR2	TAN (SEE NOTE 3)	20 ga	A7
WBI SHIELD	SHIELD (SEE NOTE 3)	20 ga	A8
WBI HTR-	YELLOW (SEE NOTE 3)	18 ga	A9
SWITCHED +12V IN	RED/WHITE	18 ga	A10
MAT INPUT	BLUE	20 ga	A11
INPUT #1 (FS2THG)	WHITE/BLUE	20 ga	A12
INPUT #3 (F G 5)	WHITE/BLACK	20 ga	A13
IPU GROUND	GREEN	20 ga	A14
DG1 TX	WHITE/BLACK	20 ga	A15
WBI COMPR1	BROWN (SEE NOTE 3)	20 ga	A16
WBI VS-/IP-	BLACK/WHITE (3)	20 ga	A17
SENSOR GROUND OUT	BLACK/WHITE (3)	20 ga	A18
COOLANT TEMP IN	BROWN	20 ga	A19
OIL PRESSURE	GREY	20 ga	A20
KNOCK #2 IN	BEIGE/RED	20 ga	A21
CAN INPUT (DIG & IPU)	PURPLE	20 ga	A22
MAP SENSOR SIGNAL	RED/BLACK	20 ga	A23
CAN LO	ORANGE	20 ga	A24
WBI VS+	RED (SEE NOTE 3)	20 ga	A25
SENSOR +5V REF OUT	ORANGE	20 ga	A26
BYPASS OUT	BEIGE/BLACK	20 ga	A27
EST/SPOUT OUT	BLUE/WHITE	20 ga	A28
KNOCK #1 INPUT	BEIGE/BLUE	20 ga	A29
CRANK INPUT (DIG & IPU)	PURPLE	20 ga	A30
FUEL PRESSURE	PURPLE	20 ga	A31
CAN HI	ORANGE/BLACK	20 ga	A32
WBI IP+	WHITE (SEE NOTE 3)	20 ga	A33
WBI HTR+	ORANGE (SEE NOTE 3)	18 ga	A34

DESCRIPTION	COLOR	WIRE GAUGE	PIN
IAC A LO	PURPLE/BLUE	20 ga	B1
IAC A HI	PURPLE/YELLOW	20 ga	B2
PWM #4 OUT (HG)	GREY/GREEN	20 ga	B3
INJECTOR F	GREEN	20 ga	B4
INJECTOR G	ORANGE	20 ga	B5
INJECTOR H	BLUE	20 ga	B6
INJECTOR E	PINK	20 ga	B7
IAC B LO	PURPLE/WHITE	20 ga	B8
IAC B HI	PURPLE/BLACK	20 ga	B9
PWM #3 OUT (HG)	GREY/BLACK	20 ga	B10
PWM #2 OUT (HG)	GREY/RED	20 ga	B11
PWM #1 OUT (HG)	GREY/YELLOW	20 ga	B12
INJECTOR D	PURPLE	20 ga	B13
EST GROUND OUT	BLACK/YELLOW	20 ga	B14
EST B	GREEN/WHITE	20 ga	B15
EST D	ORANGE/WHITE	20 ga	B16
EST F	BLUE/WHITE	20 ga	B17
EST H	PINK/WHITE	20 ga	B18
INJECTOR A	GREY	20 ga	B19
EST 12V OUT	RED/YELLOW	20 ga	B20
EST A	YELLOW/WHITE	20 ga	B21
EST C	GREY/WHITE	20 ga	B22
EST E	LIGHT BLUE/WHITE	20 ga	B23
EST G	LIGHT GREEN/WHITE	20 ga	B24
INJECTOR C	BEIGE	20 ga	B25
INJECTOR B	WHITE	20 ga	B26

POWER	WBI	MAP
A	CG	
B	A18	
C	A26	
D	FF	

INPUTS/ OUTPUTS	
A	A12
B	A3
C	A13
D	A4
E	B12
F	B11
G	B10
H	B3

	A	B	C	D	E	F	G	H
A34	A							
A9	B							
A16	C							
A7	D							
A17	E							
A33	F							
A25	G							
A8	H							

	A	B	C	D	E	F	G	H	I	J	K
A30	A										
A22	B										
A14	C										
A10	D										
A27	E										
A14	F										
A28	G										
A14	H										
A14	J										
A14	K										

	A	B	C
A18	A		
A23	B		
A26	C		

	A	B	C
A18	A		
A5	B		
A26	C		

	A	B	C	D	E	F	G	H	I	J	K
B19	A										
B26	B										
B25	C										
B13	D										
B7	E										
B4	F										
B5	G										
B6	H										
B6	I										
B6	J										
B6	K										

	A	B
B20	A	
B3	B	